



DATA SHEET

XDT AM/FM DUAL TUNER

TECHNICAL SPECIFICATIONS:

DIMENSIONS:

- Height: 3-3/4" (20 mm)
- Width: 17-1/8" (273 mm)
- Depth: 10-5/8" (89 mm)
- Weight: 9 lbs (4 kg)

CONNECTIONS:

- Analog Audio Out for TUNER1 : RCA (L, R)
- Analog Audio Out for TUNER 2 : RCA (L, R)
- IR In : Mono Mini
- FM Antenna Terminal (75ohms) Coaxial
- AM Antenna Clips
- RS232 : DB9 female

ENVIRONMENTAL:

- Temperature: <60°C
- Humidity: < 95%RH

INCLUDED ACCESSORIES:

- Remote control
- Rack ears
- FM dipole antenna
- Stereo RCA cable
- AM loop antenna
- 75 Ohm adapter

POWER REQUIREMENTS:

- 120VAC 60Hz

POWER CONSUMPTION:

- 12 Watts

TUNING RANGE:

- FM Tuning Range: 87.5MHz to 107.9MHz
(20kHz steps)
- AM Tuning Range: 530kHz to 1,710kHz
(10kHz steps)
- Frequency Response:
30Hz to 15kHz +/- 1.5dB

APPROVALS AND CERTIFICATIONS:

- CE
- C-Tick